



JDYX.E197390 - Fuses, Supplemental

Fuses, Supplemental

OPTIFUSE
 Suite C
 1675 Pioneer Way
 El Cajon, CA 92020 United States

E197390

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
Supplemental fuses: pigtail leads, cartridge enclosed				
FSA,-P	6 x 31.5 (0.24 x 1.24)	0.1-10	125Vac	10000
		0.1-10	250Vac	200
Supplemental fuses: cartridge enclosed				
FCE	4.6 x 14.2 (0.18 x 0.56)	0.1-8	125Vac	10000
		0.1-8	250Vac	200
		0.1-8	350Vac	100
FSA	6.35 x 31.75 (0.25 x 1.25)	0.01-10	125Vac	10000
		0.01-10	250Vac	200
FSC	5.2 x 20 (0.20 x 0.79)	0.01-10	125Vac	10000
		0.01-1	250Vac	35
		1.1-3.5	250Vac	100
		3.6-10	250Vac	200
FSC,-P	4.9 x 20 (0.19 x 0.79)	0.1-1.0	125Vac	10000
		0.1-1.0	250Vac	35
		1.1-8.0	125Vac	10000
		1.1-8.0	250Vac	200

Cookies on UL

We use cookies to personalize content and ads, to provide social media features and to analyze our traffic. We also share information about your use of our site with our social media, advertising and analytics partners. [Learn more](#)

Cookies Settings

Accept All Cookies

		10-10	125Vac	10000
FSE	4.6 x 14.5 (0.18 x 0.57)	0.01-3.5	125Vac	10000
		0.01-1	250Vac	35
		1.1-3.5	250Vac	100
FSG	10.3 x 38.1 (0.41 x 1.50)	0.5-3.5	125Vac	10000
		0.5-1	250Vac	35
		1.1-3.5	250Vac	100
FSH	6.35 x 15.9 (0.25 x 0.63)	0.063-3.5	125Vac	10000
		0.063-1	250Vac	35
		1.1-3.5	250Vac	100
FSX	6.35 x 25.4 (0.25 x 1.00)	0.02-10	125Vac	10000
		0.02-1	250Vac	35
		1.1-3.5	250Vac	100
		3.6-10	250Vac	200
MSA	6.35 x 31.75 (0.25 x 1.25)	0.5-8	125Vac	10000
		0.5-8	250Vac	200
MSC	5.2 x 20 (0.20 x 0.79)	0.05-10	125Vac	10000
		0.05-1.0	250Vac	35
		1.1-3.5	250Vac	100
		3.6-10	250Vac	200
TCE	4.6 x 14.2 (0.18 x 0.56)	0.1-8	125Vac	10000
		0.1-8	250Vac	200
		0.1-8	350Vac	100
TSC	5.2 x 20 (0.20 x 0.79)	0.01-8	125Vac	10000
		0.01-1	250Vac	35

		1.1-3.5	250Vac	100
		3.6-8	250Vac	200
TSC-LS	5.2 x 20 (0.20 x 0.79)	0.01-8	125Vac	10000
		0.01-1	250Vac	35
		1.1-3.5	250Vac	100
		3.6-8	250Vac	200
TSE, TSE-LS	4.6 x 14.5 (0.18 x 0.57)	0.01-8	125Vac	10000
		0.01-1	250Vac	35
		1.1-3.5	250Vac	100
		3.6-8	250Vac	200
Supplemental fuses: filled-tube				
FPK	10.3 x 38 (0.41 x 1.50)	0.1-0.375	600Vac	100000
		0.4-2	600Vac	100000
		2.5-5	600Vac	100000
		6-12	600Vac	100000
		15-30	600Vac	100000
		0.1-0.375	600Vdc	10000
		0.4-2	600Vdc	10000
		2.5-5	600Vdc	10000
		6-12	600Vdc	10000
		15-30	600Vdc	10000
TCC	5.2 x 20 (0.20 x 0.79)	0.01-15	125Vac	10000
		0.01-1.0	250Vac	35
		1.1-3.5	250Vac	100
		3.6-10	250Vac	200
		10.1-15	250Vac	750

Supplemental fuses: filled-tube, cartridge enclosed				
FCA	6.35 x 31.75 (0.25 x 1.25)	0.01-15	125Vac	10000
		0.01-15	250Vdc	750
		0.01-1	250Vac	35
		1.1-3.5	250Vac	100
		3.6-10	250Vac	200
		10.1-15	250Vac	750
FCC	5.2 x 20 (0.20 x 0.79)	0.01-15	125Vac	10000
		0.01-1	250Vac	35
		1.1-3.5	250Vac	100
		3.6-10	250Vac	200
		10.1-15	250Vac	750
TCA	6.35 x 31.75 (0.25 x 1.25)	0.1-20	125Vac	10000
		0.1-20	250Vac	1500
		0.1-30	250Vdc	300
Supplemental fuses: pigtail leads, cartridge enclosed				
FSA-P	6.35 x 31.75 (0.25 x 1.25)	0.01-10	125Vac	10000
		0.01-10	250Vac	200
FSC-P	5.2 x 20 (0.20 x 0.79)	0.01-10	125Vac	10000
		0.01-1	250Vac	35
		1.1-3.5	250Vac	100
		3.6-10	250Vac	200
FSE-P, FSE	4.6 x 14.5 (0.18 x 0.57)	0.01-3.5	125Vac	10000
		0.01-1	250Vac	35
		1.1-3.5	250Vac	100

FSH-P	6.35 x 15.9 (0.25 x 0.63)	0.063-3.5	125Vac	10000
FSX-P	6.35 x 25.4 (0.25 x 1.00)	0.02-10	125Vac	10000
		0.02-1	250Vac	35
		1.1-3.5	250Vac	100
		3.6-10	250Vac	200
MSA-P	6.35 x 31.75 (0.25 x 1.25)	0.5-8	125Vac	10000
		0.5-8	250Vac	200
MSC-P	5.2 x 20 (0.20 x 0.79)	0.05-10	125Vac	10000
		0.05-1.0	250Vac	35
		1.1-3.5	250Vac	100
		3.6-10	250Vac	200
TCE-P	4.6 x 14.2 (0.18 x 0.56)	0.1-8	125Vac	10000
		0.1-8	250Vac	200
		0.1-8	350Vac	100
TSC-LSP	5.2 x 20 (0.20 x 0.79)	0.01-8	125Vac	10000
		0.01-1	250Vac	35
		1.1-3.5	250Vac	100
		3.6-8	250Vac	200
TSC-P	5.2 x 20 (0.20 x 0.79)	0.01-8	125Vac	10000
		0.01-1	250Vac	35
		1.1-3.5	250Vac	100
		3.6-8	250Vac	200
TSE-LSP	4.6 x 14.5 (0.18 x 0.57)	0.01-3.5	125Vac	10000
		0.01-1	250Vac	35

		1.1-3.5	250Vac	100
Supplemental fuses: pigtail leads, filled-tube				
TCC-P	5.2 x 20 (0.20 x 0.79)	0.01-15	125Vac	10000
		0.01-1.0	250Vac	35
		1.1-3.5	250Vac	100
		3.6-10	250Vac	200
		10.1-15	250Vac	750
Supplemental fuses: pigtail leads, filled-tube, cartridge enclosed				
FCA-P	6.35 x 3.75 (0.25 x 0.15)	0.01-15	125Vac	10000
		0.01-15	250Vdc	750
		0.01-1	250Vac	35
		1.1-3.5	250Vac	100
		3.6-10	250Vac	200
		10.1-15	250Vac	750
FCC-P	5.2 x 20 (0.20 x 0.79)	0.01-15	125Vac	10000
		0.01-1	250Vac	35
		1.1-3.5	250Vac	100
		3.6-10	250Vac	200
		10.1-15	250Vac	750
TCA-P	6.35 x 31.75 (0.25 x 1.25)	0.1-15	125Vac	10000
		0.1-1	250Vac	35
		1.1-3.5	250Vac	100
		3.6-10	250Vac	200
		10.1-15	250Vac	750
		0.1-30	250Vdc	300
Supplemental fuses: time delay, cartridge enclosed				
TSA	6.35 x	0.2-3.0	125Vac	10000

	31.75 (0.25 x 1.25)			
		3.15-10	125Vac	10000
		0.2-1.0	250Vac	35
		1.1-3.0	250Vac	100
		3.15-3.5	250Vac	100
		3.6-10	250Vac	200
Supplemental fuses: time delay, filled-tube				
TPK Time delay. Otherwise non-time delay.	10.3 x 38 (0.41 x 1.50)	3.15-8	500Vac	10000
		9-12	500Vac	10000
		15-30	500Vac	10000
		0.3-3	500Vac	10000
Supplemental micro fuses: pigtail leads				
FCF,-P	3.3 x 9.4 (0.13 x 0.37)	0.1-0.8	250Vac	50
		0.1-10	250Vac	50
		12-15	125Vac	50
Supplemental micro fuses: cartridge enclosed				
FCF-P	3.6 x 10 (0.14 x 0.39)	0.1-8	250Vac	50
FSF	3.6 x 10 (0.14 x 0.39)	0.05-10	250Vac	50
TCF	3.6 x 10 (0.14 x 0.39)	0.1-5	250Vac	50
TSF	3.6 x 10 (0.14 x 0.39)	0.05-10	250Vac	50
Supplemental micro fuses: pigtail leads, cartridge enclosed				
FCF	3.6 x 10 (0.14 x 0.39)	0.1-8	250Vac	50
FMR,FMS	8.5 x 8.4 (0.33 x 0.33)	0.05-10	250Vac	50
FSF-P	3.6 x 10 (0.14 x 0.39)	0.05-10	250Vac	50

FXG	2.8 x 8.5 (0.11 x 0.33)	0.05-8	125Vac	50
		0.05-8	125Vdc	300
TCF-P	3.6 x 10 (0.14 x 0.39)	0.1-5	250Vac	50
TMR, TMS	8.5 x 8.4 (0.33 x 0.33)	0.04-10	250Vac	50
TSF-P	3.6 x 10 (0.14 x 0.39)	0.05-10	250Vac	50

Last Updated on 2021-07-13

The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL's Follow-Up Service. Only those products bearing the UL Mark should be considered to be Certified and covered under UL's Follow-Up Service. Always look for the Mark on the product.

UL permits the reproduction of the material contained in the Online Certification Directory subject to the following conditions: 1. The Guide Information, Assemblies, Constructions, Designs, Systems, and/or Certifications (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from the Online Certifications Directory with permission from UL" must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "© 2021 UL LLC"